


Application	lr	nterrupted	Uninterrupt	ed
Thermal Current Rating ( <sup>I</sup> th)		250A	400A §	7
Intermittent Current Rating:				
30% Duty		455A	730A §	
40% Duty		395A	630A §	
50% Duty		355A	565A §	
60% Duty		325A	515A §	Ĺ
70% Duty		300A	480A §	
Rated Fault Current Breaking Capa	city			
(in accordance with UL583*)	only	( 011) 01110 1111	no constant.	
SW201		1500A at 96V §		7
SW201N		1500A at 48V §		
Maximum Recommended Contact V	/olta	iges (U <sub>e</sub> ):		
SW201		96V	D.C.	
SW201N		48V D.C.		
Typical Voltage Drop per pole acros	s Ne	ew Contacts	at 250A:	
Normally Open			mV	
Normally Closed		40mV		
Mechanical Durability				
Coil Voltage Available (U <sub>S</sub> )		>5 x 10 <sup>6</sup> Cycles		_
(Rectifier board required for A.C.)		From 6 to 24	10V A.C./D.C.	
Coil Power Dissipation:				ſ
Highly Intermittent Rated Types		60 - 8	0 Watts	
Intermittently Rated types		30 - 6	0 Watts	ĺ
Prolonged Rated Types			0 Watts	
Continuously Rated Types			1 Watts	4
Maximum Pull-In Voltage (Coil at 20	r ° C)		i vvalis	
	<b>(</b>	Guideline.		
Highly Intermittent Rated types (Max 25% Duty Cycle)		60%	√ U <sub>S</sub>	
Intermittently Rated types		60%	∥ U <sub>s</sub>	
(Max 70% Duty Cycle) Prolonged Operation		<del>-</del>		4
(Max 90% Duty Cycle)		60%	∥U <sub>s</sub>	1
Continuously Rated Types (100% Duty Cycle)		66%	∥ U <sub>s</sub>	
Drop-Out Voltage Range		10 - 20% U <sub>S</sub>		
Typical Pull-In Time			)ms	1
(Ň/O Contacts to Close):		40	ins	4
Typical Drop-Out Time (N/O Contac	ts to	Open):		
Without Suppression		10	)ms	4
With Diode Suppression		100ms		1
With Diode and Resistor (Subject to resistance value)		30ms		
Main Contact Change over time (mil	llise	conds):		1
Normally Closed to Normally Open			ms	
Normally Open to Normally Closed			ms	
Typical Contact Bounce Period			ms	
••		-		4
Operating Ambient Temperature		- 40 C t	o + 60°C	4
Guideline Contactor Weight:				
SW201			gms gms	1
With Auxiliary		+ 20	gms	4
Without Blowouts		- 50	gms	1
Auxiliary	Deta	ails		
Auxiliary Thermal Current Rating		Ę	5A	
Auxiliary Contact Switching Capa	bili	ties (Resisti	ve Load):	
SW201A		SW	201C	
5A at 24\	/ D.	C.		
2A at 48\	/ D.	C.		ĺ
0.5A at 240		D.C.		Ĺ
Advised Connection Sizes for Ma	-		ous Current	Í
Copper busbar	7			
	<u> </u>			
Cable Rated suitable for Application				
Key: = Interrupted = Unin				
	11m c	are at 20°C		
<b>Note:</b> Where applicable values show * Please check our web site for proc				


The SW201 has been designed for direct current loads, including motors as used on electric vehicles such as industrial trucks. Developed for both interrupted and uninterrupted§ loads, the SW201 is suitable for switching Resistive, Capacitive and Inductive loads.


- Interrupted current opening and closing on load with frequent switching (results in increased contact resistance).
- Uninterrupted current no or infrequent load switching requirements (maintains a lower contact resistance).

The SW201 features single pole double throw, double breaking main contacts with silver alloy tips, which are weld resistant, hard wearing and have excellent conductivity. The SW201 has M10 stud main terminals and 6.3mm spade coil connections. It can be mounted via M4 tapped holes or mounting brackets - either supplied fitted, or as separate items. Mounting can be horizontal or vertical, when vertical the M10 contact studs should point upwards. If the requirement is for downwards orientation we can adjust the contactor to compensate for this. Please note Normally Closed contacts are not suited to make and break load.











SW201 Available Options

**Auxiliary Contacts** 

Auxiliary Contacts - V3





Magnetic Blowouts†	•	В				
Magnetic Blowouts - High Powered <sup>†</sup>	0	В				
Armature Cap	•					
Mounting Brackets (See Stud Series Catalogue)	0					
Magnetic Latching <sup>†</sup> (Not fail safe)	0	М				
Closed Contact Housing <sup>‡</sup>	0					
Environmentally Protected IP66	X					
EE Type (Steel Shroud)	0					
Contacts						
Large Tips	X					
Textured Tips	0	T				
Silver Plating	X					
Coil						
AC Rectifier Board (Fitted)	0					
Coil Suppression <sup>†</sup>	0					
Flying Leads	0	F				
Manual Override Operation	0					
M4 Stud Terminals	X					
M5 Terminal Board	0					
Vacuum Impregnation	0					
<b>Key:</b> Optional ○ Standard • Not Available X						
† Connections become polarity sensitive						
<sup>‡</sup> Open Housing Available						

Albright reserve the right to change data without prior notice

from figures may be necessary according to application.

Suffix

Α

0

0